



VAX-D6.4R HIGH-SECURITY CONTACTLESS SMARTCARD READER

This Quick Start Guide is intended for experienced installing technicians. It is a basic reference to ensure all connections are properly made. It is for model VAX-D6.4R. For additional information please refer to Vicon's website vicon-security.com.

1.0 Introduction

A key component of a physical security electronic access control system, a contactless smartcard reader is based on RFID technology. In operation it is capable of reading data stored on a proximity credential via radio frequency and without physical contact, and then passing the data obtained to the physical access control system. Access control systems typically manage and record the movement of individuals through a protected area, such as a locked door.

2.0 Mounting Provisions

Each reader may be installed either indoors or outdoors. Mounting options shown in the table below. Use supplied #6 mounting screws, or equivalent security screws, for installation.

| Model | Mullion Mount | Single-Gang Wall Mount* |
|-----------|---------------|-------------------------|
| VAX-D6.4R | | • |

*Plastic or metal.

3.0 Reader Wiring

| Wiegand | | Magstripe | |
|-----------|------------------------|-----------|---------------|
| Conductor | Function | Conductor | Function |
| Red | DC (8-14 VDC) | Red | DC (8-14 VDC) |
| Black | Ground | Black | Ground |
| Green | Data 0 | Green | Clock |
| White | Data 1 | White | Data |
| Brown | Red LED ^a | Brown | Red LED |
| Orange | Green LED ^b | Orange | Green LED |
| Yellow | Card Present | Yellow | Card Present |
| Blue | Beeper | Blue | Beeper |
| Violet | Read Mode ^c | Violet | Read Mode |
| Drain | Shield Ground | Drain | Shield Ground |

4.0 Cable Requirements

24 AWG minimum, multi-conductor stranded with an overall foil shield, for example Belden 9535 or similar, supporting the five conductors comprising the physical layer of the Wiegand interface (power, ground, data 0, data 1, and/or beeper and LED). Alternatively, Belden 9539 or similar, for all reader functions. Contact your access control system manufacturer for their specific requirements. Per the SIA's Wiegand specification, maximum cable length is 500 feet (152 m).

5.0 Output Formats

- Wiegand (industry standard 26-bit Wiegand and custom Wiegand formats)
- Magnetic Stripe (ABA Track II, clock and data, with card present)

6.0 Grounding

Shield (drain) continuity must run from the reader to the access panel. Shield (drain) and reader ground must be tied together at the access panel and connect to an earth ground at one point.

7.0 Power

Reader may be powered by the access panel. A linear power supply is recommended for best operation.

8.0 Voltage and Current

Voltage: 8 to 14 VDC

Current Draw: 135mA typical at 12 VDC

9.0 Read Mode

For sector data reads, pull the purple conductor low.

10.0 Connection

Connection must be done in accordance with NFPA 70. Do not connect to a receptacle controlled by a switch. Connect to a power limited DC voltage source.

11.0 Troubleshooting

1. When the reader is first powered on it will beep 4-times, and the LED will shine red.
2. Presenting a supported access credential will result in the reader beeping and the LED flashing once.

NOTE: The access panel controls LED functionality, such as switching the LED to green.

WIRING NOTES:

^a**Single Line LED:** This is the standard operating mode and does not make use of the Orange conductor. The LED is Red when the reader is idle and flashes when a card is presented. The LED turns Green when the Brown Conductor is pulled low by the access control panel.

^b**Dual Line LED:** This mode makes use of both the Brown and Orange conductors. The Brown conductor controls the Red LED and the Orange conductor controls the Green LED. LED states are determined by the access control system option and capability.

Unused conductors should be trimmed, isolated and taped back to prevent unintended current flows. Apply positive voltage only to the Red DC Conductor.

QUICK START GUIDE

VAX-D6.4R HIGH-SECURITY CONTACTLESS SMARTCARD READER

If the reader does not recognize the card or tag (no beep, no LED flash) or exhibits short read range, please see the table below for possible causes and solutions.

| Possible Cause | Corrective Action |
|---|---|
| Incorrect cabling | Verify gauge, connections and cabling length |
| Not enough power | 12 VDC recommended |
| Incorrect card used | Verify if card technology is supported |
| Reader/access panel not properly grounded | Earth ground needed—verify shield and reader ground are tied at access panel and connect to ground at one point |
| Supply generating interference | Linear power supply recommended, verify switching power supply before use |

Should any of the corrective actions mentioned above not improve performance, disconnect the reader from the access panel and power it with a separate power supply or 9 VDC battery and re-test card functionality. By powering the readers separately, most variables that may lead to reduced performance can be eliminated. Should the problem persist, please contact Vicon Technical Support.

IP Rating: IP67-rated for outdoor use

Many Vicon Readers carry the following certifications:



FCC Compliance Statement: This device complies with part 15 of the FCC rules. Operation is subject to the following two conditions: (1) this device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

Caution: Changes or modifications not expressly approved by Vicon Industries could void the user's authority to operate the equipment.

Product can be used without license conditions or restrictions in all European Union countries, including Austria, Belgium, Bulgaria, Cyprus, Czech Republic, Denmark, Estonia, Finland, France, Germany, Greece, Hungary, Ireland, Italy, Latvia, Lithuania, Luxembourg, Malta, Netherlands, Poland, Portugal, Romania, Slovakia, Spain, Sweden, United Kingdom, as well as other non-EU countries, including Iceland, Norway, and Switzerland.

This device complies with Industry Canada licence-exempt RSS standard(s). Operation is subject to the following two conditions: (1) this device may not cause interference, and (2) this device must accept any interference, including interference that may cause unde-sired operation of the device.

Cet appareil est conforme à Industrie Canada exempts de licence standard RSS (s). Le fonctionnement est soumis aux deux conditions suivantes : (1) ce dispositif ne peut pas provoquer d'interférences et (2) ce dispositif doit accepter toute interférence, y compris les interférences qui peuvent causer un mauvais fonctionnement du dispositif.

Note: This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instruction manual, may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference in which case the user will be required to correct the interference at his own expense.

For proper PIN security with keypad readers, please review [PIN Best Practices Reference Document](#).

Vicon Industries Inc.

Tel: 631-952-2288
Toll Free: 800-645-9116
Fax: 631-951-2288

24-Hour Technical Support:
800-34-VICON (800-348-4266)
UK: 44/(0) 1489-566300