



Product at a Glance

- ▶ Omni-directional microphone (within 30 ft/9 m diameter)
- ▶ Built-in speaker
- ▶ Vandal-resistant call button
- ▶ Provides bi-directional audio
- ▶ Designed for outdoor use

The IQACCESS-INT intercom box provides audio capability for IQeye cameras using the IQaccess software. It is designed to interface with audio/video transmission systems.

The unit contains a built-in microphone and 4-inch speaker for providing bi-directional audio with the IP network camera (receiving source). A vandal resistant call button for switch closure activity is provided. Gain adjust potentiometers for listen and talkback are located inside the unit.

The IQACCESS-INT is designed for wall mounting and is supplied with two back boxes, one for surface mounting (metal) and one for flush mounting (plastic).

SPECIFICATIONS

Microphone

Type:	Electret condenser
Audio Output:	Line level (0 dB @ 600Ω) unbalanced
Element Sensitivity:	-45 dB
Frequency Response:	40 Hz - 15 kHz
Audio Input Impedance:	600Ω

Speaker

Speaker Power Output:	1 W
Speaker Impedance:	8Ω
Speaker Magnet:	1.73 oz. ceramic
Speaker Size:	4 in. (102 mm)
Current Drain:	200 mA
Supply Voltage:	12 VDC
Dimensions:	Faceplate: 8 in. (H) x 6.25 in. (W) (203 mm x 159 mm) Metal Backbox: 8 in. (H) x 6.25 in. (W) x 2.75 in. (D) (203 mm x 159 mm x 699 mm) Plastic Backbox: 8 in. (H) x 6.25 in. (W) x 2.625 in. (D) (203 mm x 159 mm x 667 mm)

Weight: 1.45 lb (0.7 kg)